

# SYSMAC CP-series Programmable Controllers Safety Precautions

OMRON

## OMRON Corporation

©OMRON Corporation 2007 All Rights Reserved

1118339-0E

Thank you for purchasing an OMRON Programmable Controller (PLC). To ensure safe operation, please be sure to read the safety precautions provided in this document along with all of the user manuals for the Programmable Controller. Please be sure you are using the most recent versions of the user manuals. Contact your nearest OMRON representative to obtain manuals. Keep these safety precautions and all user manuals in a safe location and be sure that they are readily available to the final user of the products.

### ■ General Precautions

The user must operate the product according to the performance specifications described in the operation manuals.

Before using the product under conditions which are not described in the manual or applying the product to nuclear control systems, railroad systems, aviation systems, vehicles, combustion systems, medical equipment, amusement machines, safety equipment, petrochemical plants, and other systems, machines, and equipment that may have a serious influence on lives and property if used improperly, consult your OMRON representative.

Make sure that the ratings and performance characteristics of the product are sufficient for the systems, machines, and equipment, and be sure to provide the systems, machines, and equipment with double safety mechanisms.

### ■ Safety Precautions

#### Definition of Precautionary Information

**⚠ DANGER** Indicates an imminently hazardous situation, which, if not avoided, will result in death or serious injury.

**⚠ WARNING** Indicates a potentially hazardous situation, which, if not avoided, could result in death or serious injury.

**⚠ Caution** Indicates a potentially hazardous situation, which, if not avoided, may result in minor or moderate injury, or property damage.

#### Warnings and Cautions

**⚠ WARNING** Do not attempt to take any Unit apart while the power is being supplied. Doing so may result in electric shock.

**⚠ WARNING** Do not touch any of the terminals or terminal blocks while the power is being supplied. Doing so may result in electric shock.

**⚠ WARNING** Do not attempt to disassemble, repair, or modify any Units. Any attempt to do so may result in malfunction, fire, or electric shock.

**⚠ WARNING** Provide safety measures in external circuits, i.e., not in the Programmable Controller (CPU Unit including associated Units; referred to as "PLC"), in order to ensure safety in the system if an abnormality occurs due to malfunction of the PLC or another external factor affecting the PLC operation. Not doing so may result in serious accidents.

• Emergency stop circuits, interlock circuits, limit circuits, and similar safety measures must be provided in external control circuits.

• The PLC will turn OFF all outputs when its self-diagnosis function detects any error or when a severe failure alarm (FALS) instruction is executed. As a countermeasure for such errors, external safety measures must be provided to ensure safety in the system.

• The PLC outputs may remain ON or OFF due to deposition or burning of the output relays or destruction of the output transistors. As a countermeasure for such problems, external safety measures must be provided to ensure safety in the system.

• When the 24-VDC output (service power supply to the PLC) is overloaded or short-circuited, the voltage may drop and result in the outputs being turned OFF. As a countermeasure for such problems, external safety measures must be provided to ensure safety in the system.

**⚠ WARNING** Fail-safe measures must be taken by the customer to ensure safety in the event of incorrect, missing, or abnormal signals caused by broken signal lines, momentary power interruptions, or other causes. Not doing so may result in serious accidents.

**⚠ WARNING** Do not apply the voltage or current outside the specified range to this unit. It may cause a malfunction or fire.

**⚠ Caution** Pay careful attention to the polarities (+/-) when wiring the DC power supply. A wrong connection may cause malfunction of the system.

**⚠ Caution** Execute online edit only after confirming that no adverse effects will be caused by extending the cycle time. Otherwise, the input signals may not be readable.

**⚠ Caution** Confirm safety at the destination node before transferring a program to another node or editing the I/O area. Doing either of these without confirming safety may result in injury.

**⚠ Caution** Tighten the screws on the terminal block of the AC Power Supply Unit to the torque specified in the operation manual. The loose screws may result in burning or malfunction.

**⚠ Caution** Do not touch anywhere near the power supply parts or I/O terminals while the power is ON, and immediately after turning OFF the power. The hot surface may cause burn injury.

**⚠ Caution** After programming (or re-programming) using the IOWR instruction, confirm that correct operation is possible with the new ladder program and data before starting actual operation. Any irregularities may cause the product to stop operating, resulting in unexpected operation in machinery or equipment.

**⚠ Caution** The contents of user memory are saved in non-volatile memory even when the battery is low or when no battery is inserted in the CPU Unit. (Operation will not stop due to a memory error.) Accordingly, the PLC System can be operated even when the battery is low or no battery is inserted. The I/O memory areas backed up by the battery (including the DM, HR, and CNT Areas), however, will be unstable in this condition. If the contents of these I/O memory areas are output by the program, use the Battery Error Flag to take suitable actions, such as stopping the outputs.

### ■ Operating Environment Precautions

**⚠ Caution** Do not operate the control system in the following places:

- Locations subject to direct sunlight
- Locations subject to temperatures or humidity outside the range specified in the specifications
- Locations subject to condensation as the result of severe changes in temperature
- Locations subject to corrosive or flammable gases
- Locations subject to dust (especially iron dust) or salts
- Locations subject to exposure to water, oil, or chemicals
- Locations subject to shock or vibration

**⚠ Caution** Take appropriate and sufficient countermeasures when installing systems in the following locations:

- Locations subject to static electricity or other forms of noise
- Locations subject to strong electromagnetic fields
- Locations subject to possible exposure to radioactivity
- Locations close to power supplies

**⚠ Caution** The operating environment of the PLC System can have a large effect on the longevity and reliability of the system. Improper operating environments can lead to malfunction, failure, and other unforeseeable problems with the PLC System. Be sure that the operating environment is within the specified conditions at installation and remains within the specified conditions during the life of the system.

### ■ Application Precautions

**⚠ WARNING** Always heed these precautions. Failure to abide by the following precautions could lead to serious or possibly fatal injury.

- Always connect to 100 Ω or less when installing the Units. Not connecting to a ground of 100 Ω or less may result in electric shock.
- Always turn OFF the power supply to the PLC before attempting any of the following.
  - Not turning OFF the power supply may result in malfunction or electric shock.
  - Mounting or dismantling Expansion Units or any other Units
  - Connecting or removing the Memory Cassette or Option Board
  - Setting DIP switches or rotary switches
  - Connecting or wiring the cables
  - Connecting or disconnecting the connectors

**⚠ Caution** Failure to abide by the following precautions could lead to faulty operation of the PLC or the system, or could damage the PLC or PLC Units. Always heed these precautions.

- Always use the power supply voltage specified in the operation manuals. An incorrect voltage may result in malfunction or burning.
- Take appropriate measures to ensure that the specified power with the rated voltage and frequency is supplied. Be particularly careful in places where the power supply is unstable. An incorrect power supply may result in malfunction.

- Install external breakers and take other safety measures against short-circuiting in external wiring. Insufficient safety measures against short-circuiting may result in burning.
- Do not apply voltages or connect loads to the output terminals in excess of the maximum switching capacity. Excess voltage or loads may result in burning.
- Disconnect the functional ground terminal when performing withstand voltage tests. Not disconnecting the functional ground terminal may result in burning.
- Install the Unit properly as specified in the operation manual. Improper installation of the Unit may result in malfunction.
- Be sure that all the terminal screws and cable connector screws are tightened to the torque specified in the relevant manuals. Incorrect tightening torque may result in malfunction.

The applicable tightening torque is 2.5 Lb In. (0.28 N·m) for CP1W-CIF11/CIF12.

- Use crimp terminals for wiring. Do not connect bare stranded wires directly to terminals. Connection of bare stranded wires may result in burning.
- Wire correctly and double-check all the wiring or the setting switches before turning ON the power supply. Incorrect wiring may result in burning.
- Mount the Unit only after checking the connectors and terminal blocks completely.
- Be sure that the terminal blocks, connectors, Option Boards, and other items with locking devices are properly locked into place. Improper locking may result in malfunction.
- Check the user program for proper execution before actually running it on the Unit. Not checking the program may result in an unexpected operation.
- Check that the DIP switches and data memory (DM) are properly set before starting operation.
- Confirm that no adverse effect will occur in the system before attempting any of the following. Not doing so may result in an unexpected operation.
  - Changing the operating mode of the PLC (including the setting of the startup operating mode).
  - Force-setting/force-resetting any bit in memory.
  - Changing the present value of any word or any set value in memory.

- Resume operation only after transferring to the new CPU Unit and/or Special I/O Units the contents of the DM, HR, and CNT Areas required for resuming operation. Not doing so may result in an unexpected operation.
- Do not pull on the cables or bend the cables beyond their natural limit. Doing either of these may break the cables.
- Do not place objects on top of the cables. Doing so may break the cables.
- When replacing parts, be sure to confirm that the rating of a new part is correct. Not doing so may result in malfunction or burning.

- Before touching the Unit, be sure to first touch a grounded metallic object in order to discharge any static built-up. Not doing so may result in malfunction or damage.
- Do not touch the Expansion I/O Unit Connecting Cable while the power is being supplied in order to prevent malfunction due to static electricity.
- Do not turn OFF the power supply to the Unit while data is being transferred.
- When transporting or storing the product, cover the PCBs and the Units or put there in the antistatic bag with electrically conductive materials to prevent LSIs and ICs from being damaged by static electricity, and also keep the product within the specified storage temperature range.

- Do not touch the mounted parts or the rear surface of PCBs because PCBs have sharp edges such as electrical leads.
- Double-check the pin numbers when assembling and wiring the connectors.
- Wire correctly according to specified procedures.
- Do not connect pin 6 (+5V) on the RS-232C Option Board on the CPU Unit to any external device other than the NT-AL001 or CJ1W-CIF11 Conversion Adapter. The external device and the CPU Unit may be damaged.

- Use the dedicated connecting cables specified in operation manuals to connect the Units. Using commercially available RS-232C computer cables may cause failures in external devices or the CPU Unit.

- Check that data link tables and parameters are properly set before starting operation. Not doing so may result in unexpected operation. Even if the tables and parameters are properly set, confirm that no adverse effects will occur in the system before running or stopping data links.

- Transfer a routing table to the CPU Unit only after confirming that no adverse effects will be caused by restarting CPU Bus Units, which is automatically done to make the new tables effective.

- The user program and parameter area data in the CPU Unit is backed up in the built-in flash memory. The BKUP indicator will light on the front of the CPU Unit when the backup operation is in progress. Do not turn OFF the power supply to the CPU Unit when the BKUP indicator is lit. The data will not be backed up if power is turned OFF.

- Do not turn OFF the power supply to the PLC while the Memory Cassette is being accessed. Doing so may corrupt the data in the Memory Cassette. The 7-segment LED will light to indicate writing progress and the BKUP indicator will light while the Memory Cassette is being accessed. Wait for the 7-segment LED display and the BKUP indicator to go out before turning OFF the power supply to the PLC.

- When replacing the battery for a Unit, be sure to follow the procedure described in that Unit's operation manual.

- Always use the following size wire when connecting I/O Units, Special I/O Units, and CPU Bus Units: AWG22 to AWG18 (0.32 to 0.82 mm<sup>2</sup>).

- Dispose of the product and batteries according to local ordinances as they apply.



「廢電池請回收」

Have qualified specialists properly dispose of used batteries as industrial waste.

- The following precaution must be displayed on all products containing lithium primary batteries with a perchlorate content of 6 ppb or higher when exporting them to or shipping them through California, USA.

Perchlorate Material - special handling may apply. See <http://www.dtsc.ca.gov/hazardouswaste/perchlorate>

The CP1L-@@@-@ contains a lithium primary battery with a perchlorate content of 6 ppb or higher. When exporting a product containing the CP1L-@@@-@ to or shipping such a product through California, USA, label all packing and shipping containers appropriately.

- This product is EMC compliant when assembled in a complete PLC system of the specified PLC Series. For earthing, selection of cable, and any other conditions for EMC compliance, refer to the manual for installation.
- This is a class A product. In residential areas it may cause radio interference, in which case the user may be required to take adequate measures to reduce interference.
- Don't push the buttons and LCD with sharp things.

## ■ Optional Products

- Be sure to install the following optional products in the PLC before use.

Optional product	Applicable PLC	Applicable PLC
RS-232C Option Board CP1W-CIF01	CP1L CPU Unit	CP1H CPU Unit
RS-422A/485 Option Board CP1W-CIF11/CIF12	CP1L-□□□□-□	CP1H-□□□□-□
Data Access Module CP1W-DAM01		
Memory Cassette CP1W-ME05M		
I/O Connection Cable CP1W-CN811		
CJ-series Unit Adapter CP1W-EXT01		

## ■ CJ-series Unit Connection Precautions

- When connecting the CJ-series Unit Adapter to a CJ-series Special I/O Unit, or CPU Bus Unit, slide the upper and lower sliders until a click sound is heard to lock them securely. Desired functionality may not be achieved unless Units are securely locked in place.
- Be sure to mount the end cover supplied with the CJ-series Unit Adapter to the right-most CJ-series Unit. Unless the end cover is properly mounted, the Units may not function properly.

## ■ Reference Manuals

Please be sure to read the related user manuals in order to use the PLC safely and properly. Be sure you are using the most current version of the manual.

Name	Cat No.
SYSMAC CP-series CP1H Programmable Controllers Operation Manual	W450
SYSMAC CP-series CP1L Programmable Controllers Introduction Manual	W461
SYSMAC CP-series CP1L Programmable Controllers Operation Manual	W462
SYSMAC CP-series CP1H/CP1L Programmable Controllers Programming Manual	W451
SYSMAC CS/CJ-series Communications Commands Reference Manual CS1G/H-CPU□□-EV1, CS1G/H-CPU□□H, CS1W-SCB21-V1/41-V1, CS1W-SCU21-V1, CJ1G-CPU□□, CJ1G/H-CPU□□H, CJ1M-CPU□□□, CJ1W-SCU21-V1/41-V1, CP1H-X40D□-□, CP1H-XA40D□-□, CP1H-Y20DT-D	W342
SYSMAC CS/CJ-series Serial Communications Boards/Units Operation Manual CS1W-SCB21-V1/41-V1, CS1W-SCU21-V1, CJ1W-SCU21-V1/41-V1	W336
SYSMAC CS/CJ-series Ethernet Unit Operation Manual CS1W-ETN01/11, CJ1W-ETN11	W343
SYSMAC CS/CJ-series Ethernet Unit (100Base-TX Type) CS1W-ETN21, CJ1W-ETN21 Operation Manual Construction of Networks	W420
DeviceNet Operation Manual	W267
SYSMAC CS/CJ-series DeviceNet Unit Operation Manual CS1W-DRM21(-V1), CJ1W-DRM21	W380
CompoBus/S Operation Manual C200HW-SRM21-V1, CJ1W-SRM21, CQM1-SRM21-V1	W266
SYSMAC CS/CJ-series Controller Link Units, Repeater Units Operation Manual CS1W-CLK21-V1 (wired), CJ1W-CLK21-V1 (wired) CS1W-RPT01/02/03	W309
SYSMAC CS/CJ-series Analog I/O Units Operation Manual CS1W-PTS□□/PTW□□/PDC□□/PTR□□/PPS□□/PMV□□ CJ1W-PTS□□/PDC□□	W368
SYSMAC CS/CJ-series Analog I/O Units Operation Manual CS1W-AD041(-V1)/081(-V1), CS1W-DA041/08V/08C, CS1W-MAD44, CJ1W-AD041-V1/081(-V1), CJ1W-DA021/041/08V/08C, CJ1W-MAD42	W345
SYSMAC CJ-series Temperature Control Unit Operation Manual CJ1W-TC001/002/003/004/101/102/103/104	W396
SYSMAC CJ-series High-speed Counter Unit Operation Manual CJ1W-CT021	W401
SYSMAC CJ-series Position Control Unit Operation Manual CJ1W-NC113/213/413/133/233/433	W397
SYSMAC CJ-series Position Control Units Operation Manual CJ1W-NCF71	W426
SYSMAC CJ-series Motion Control Units Operation Manual CJ1W-MCH71	W435
SYSMAC CX-Programmer Ver. 7.1 Operation Manual WS02-CXPC1-E-V61	W446
SYSMAC CX-Programmer Ver. 7.1 Operation Manual Function Blocks CS1-H, CJ1-H, CJ1M, CP1H CPU Units WS02-CXPC1-E-V61	W447
CX-Protocol Ver. 1.7 Operation Manual WS02-PSTC1-E	W344
CX-Simulator Ver. 1.7 Operation Manual WS02-CIMC1-E	W366



**OMRON Corporation** (Manufacturer)  
Shiokoji Horikawa, Shimogyo-ku,  
Kyoto, 600-8530 Japan  
Contact: [www.ia.omron.com](http://www.ia.omron.com)

### Regional Headquarters

**OMRON EUROPE B.V.** (Importer in EU)  
Wegalaan 67-69-2132 JD Hoofdorp  
The Netherlands  
Tel: (31)2356-81-300  
Fax: (31)2356-81-388

**OMRON ELECTRONICS LLC**  
One Commerce Drive Schaumburg,  
IL 60173-5302 U.S.A.  
Tel: (1)847-843-7900  
Fax: (1)847-843-7787

**OMRON ASIA PACIFIC PTE. LTD.** No.438A Alexandra Road #05-05/08 (Lobby 2), Alexandra Technopark, Singapore 119967  
Tel: (65)6835-3011  
Fax: (65)6835-2711

**OMRON (CHINA) CO., LTD.** Room 2211, Bank of China Tower, 200 Yin Cheng Zhong Road, PuDong New Area, Shanghai, 200120 China  
Tel: (86)21-5037-2222  
Fax: (86)21-5037-2200

**Note:** Specifications subject to change without notice.

Printed in China

SYSMAC  
CPシリーズ

安全上のご注意

このたびは当社のプログラマブルコントローラ (PLC) をお買い求めいただきまして誠にありがとうございました。  
安全にご使用いただくために、本紙と PLC 本体のマニュアルおよび当該ユニットの参照マニュアルを必ずお読みください。  
参照マニュアルは、当社の最寄りの営業所に連絡し、最新のものをご使用ください。  
また本紙と参照マニュアルは、大切に保管していただくとともに、最終ユーザ様までお届けくださいますようお願いいたします。

オムロン株式会社

© OMRON Corporation 2007 All Rights Reserved. 1118339-0E

安全上のご注意

● 警告/注意表示の意味



警告

正しい取扱いをしなければ、この危険のために、軽症・中程度の傷害を負ったり、万一の場合には重症や死亡に至る恐れがあります。また、同様に重大な物的損害をもたらす恐れがあります。



注意

正しい取扱いをしなければ、この危険のために、時に軽症・中程度の傷害を負ったり、あるいは物的損害を受ける恐れがあります。

● 警告表示



警告

通電中はユニットを分解したり内部に触れたりしないでください。  
感電の恐れがあります。



通電中は端子に触れないでください。  
感電の恐れがあります。



プログラマブルコントローラ (CPU ユニットおよび各ユニットを含む、以下 PLC といいます) の故障や外部要因による異常が発生した場合も、システム全体が安全側に動くように、PLC の外部で安全対策を施してください。



異常動作により、重大な事故につながる恐れがあります。

- (1) 非常停止回路、インターロック回路、リミット回路など、安全保護に関する回路は、必ず PLC 外部の制御回路で構成してください。
- (2) PLC は、自己診断機能で異常を検出したときや、運転停止故障診断 (FALS) 命令を実行したとき、運転を停止して全出力を OFF にします。  
このとき、システムが安全側に動作するよう、PLC 外部で対策を施してください。
- (3) 出力レレーの溶着や焼損、出力トランジスタの破壊などによって、PLC の出力が ON または OFF になったままになることがあります。  
このとき、システムが安全側に動作するよう、PLC 外部で対策を施してください。
- (4) PLC の DC24V 出力 (サービス電源) が過負荷の状態または短絡されると、電圧が降下し出力は OFF となることがあります。  
このとき、システムが安全側に動作するよう、PLC 外部で対策を施してください。

信号線の断線、瞬時停電による異常信号などに備えて、ご使用者側でフェールセーフ対策を施してください。  
異常動作により重大な事故につながる恐れがあります。



ユニットに入力する電圧/電流は定められた範囲で入力してください。  
範囲外の電圧/電流を使用すると故障や火災の原因となります



注意

サイクルタイムが延びても影響がないことを確認してから、オンラインエディットをしてください。  
入力信号を読み取れないことがあります。



他ノードへプログラムを転送するときや、I/O メモリを変更する操作をするときは、変更先ノードの安全を確認してから行ってください。けがをする恐れがあります。



AC 電源の端子ねじは参照マニュアルで指定した規定トルクで締めてください。  
ねじが緩むと発火および誤動作の恐れがあります。



通電中や電源を切った直後は、電源部や入出力端子部の周辺に触れないでください。火傷の恐れがあります。



直流電源を配線するときは、+/- 極性に注意してください。  
接続を誤ると、システムが異常動作をする恐れがあります。



PLC をパソコンなどの周辺機器に接続するときは、外部電源を 0V 側で接地するか、または接地しないでください。  
周辺機器の接地方法によっては外部電源が短絡する恐れがあります。



IOWR 命令によるユニットの設定 (再設定) を行う場合は、作成したラダープログラムおよびデータは十分な動作確認を行ったうえで本運転を行ってください。  
設定データに不正がある場合、ユニットは運転を停止し、装置や機械が想定外の動作をする恐れがあります。



CPU ユニットのバッテリー電圧低下時およびバッテリー非実装時もユーザメモリは不揮発性メモリに保存されます (メモリ異常による運転停止は行いません)。  
したがって、バッテリー電圧低下時やバッテリー非実装時も運転は可能ですが、バッテリーで保持される I/O メモリエリア (DM/HR/CNT を含む) は不定となります。  
ラダープログラムで DM などの I/O メモリエリアの内容を参照して外部へ出力する場合は、「電池異常フラグ」を用いて出力を止めるなどの対策を施してください。



安全上の要点

- 外部配線の短絡に備えて、ブレーカを設置するなど安全対策を施してください。
- 端子台、コネクタは十分確認してから装着してください。
- PLC の端子台のねじ、ケーブルのねじは、参照マニュアルで指定した規定トルクで締めてください。形 CP1W-CIF11/CIF12 の端子台ねじは 0.28N・m (2.5Lb In.) で締め付けてください。
- 参照マニュアルに示すとおり、正しく配線してください。
- 参照マニュアルで指定した電源電圧で使用してください。
- 電源事情が悪い場所では特に、定格の電圧や周波数の電源が供給できるようにしてご使用ください。
- 配線は圧着端子を付けてください。撚り合わせただけの電線を、直接端子台に接続しないでください。
- 出力端子には、最大開閉能力を超える電圧の印加および負荷の接続をしないでください。
- 据え付け工事の際には、必ず D 種接地 (第 3 種接地) をしてください。
- 端子台、コネクタ、オプションボードなどロック機構のあるものは、必ずロックしていることを確認してからご使用ください。
- 耐電圧試験は、機能接地端子を外して行ってください。
- 配線、スイッチなどの設定を十分確認してから通電してください。
- 運転を開始する前に、ディップスイッチやデータメモリ (DM) が正しく設定されていることを確認してください。
- 作成したユーザプログラムは、十分な動作確認を行った後、本運転に移行してください。
- 運転再開に必要なデータメモリ (DM) や保持リレーの内容、プログラム、パラメータおよびデータは、交換した CPU ユニット、高機能 I/O ユニットに転送してから運転を再開してください。
- 本製品を分解して修理や改造をしないでください。
- 次のことを行うときは、PLC 本体の電源を OFF にしてください。
  - ・ 拡張ユニットを CPU ユニットから着脱するとき
  - ・ メモリカセットやオプションボードを着脱するとき
  - ・ ディップスイッチやロータリースイッチを設定するとき
  - ・ ケーブルを接続、配線するとき
  - ・ コネクタを取り付けたり、取り外したりするとき
- 次の操作は設備に影響がないかを確認したうえで行ってください。
  - ・ PLC の動作モード切り替え (電源投入時の動作モード設定を含む)
  - ・ 接点の強制セット/リセット
  - ・ 現在値や設定値の変更
- ケーブルを無理に曲げたり引っ張ったりしないでください。
- ケーブルやコードにものを載せないでください。
- 部品の交換は、必ず定格が正しいことを確認した上で行ってください。
- 接地された金属に触れるなどして、人体の静電気を放電させてからユニットに触れてください。
- 静電気による誤動作防止のため、通電中は拡張 I/O 接続ケーブルに触れないでください。
- データの転送中はユニットの電源を OFF にしないでください。
- 運搬や保存時は、LSI、IC など、静電気による破壊防止のため、ユニットや回路基板を導電性のもので覆うか、帯電防止袋に入れ、保存温度範囲に保ってください。
- 回路基板には電気部品のリードなど鋭利な部分がありますので、部品実装部や基板の裏面に直接手を触れないでください。
- コネクタの組み立て、配線はピン番号を十分確認してから行ってください。
- 配線は参照マニュアルで指示された方法で行ってください。
- CPU ユニットに装着した RS-232C オプションボードの 6 番ピン (+5V 電源) は、変換アダプタ 形 CJ1W-CIF11/形 NT-AL001 以外の外部機器には接続しないでください。外部機器および CPU ユニットが故障する恐れがあります。
- 接続ケーブルは各ユニットのマニュアルに記載されている専用ケーブルを使用してください。市販の一般パソコン用 RS-232C ケーブルを使用すると、外部機器および CPU ユニットが故障する恐れがあります。

- 不適切なデータリンクテーブルパラメータが設定されていると、設備が予期しない動作をする恐れがあります。また、適切なデータリンクテーブルパラメータが設定されている場合でも、設備に影響がないことを確認してから転送を実行してください。
- ルーチングテーブルを周辺ツールから PLC に転送すると、CJ シリーズ CPU 高機能ユニットにリセットがかかります。これは設定したルーチングテーブルを読み込んで有効にするためです。リセットがかかっても設備に影響がないことを確認してからデータリンクテーブルを起動/停止してください。
- ユーザプログラムやパラメータエリアのデータは内蔵フラッシュメモリにバックアップされます。バックアップ中は CPU ユニット前面の BKUP LED が点灯します。点灯中は PLC 本体の電源を切らないでください。万一切ったときは、データはバックアップされません。
- メモリカセット書込み中に PLC 本体の電源を切らないでください。メモリカセット内のデータが不正となる可能性があります。メモリカセット書込み中は7セグメントLEDで書込みの進行状況を点灯表示し、BKUP LED が点灯します。7セグメントLEDから書込み中の表示が消灯した後、またはBKUP LED が消灯した後に PLC 本体の電源を切ってください。
- メモリの内容が破壊される可能性があるため、電池の交換前は5分以上通電し、電源OFF後5分以内に新しい電池と交換してください。
- 入出力端子に接続する配線材は、必ず以下のものを使用してください。AWG22-18 (0.32~0.82 mm<sup>2</sup>)
- 本体および不要になった電池の廃棄については、地方自治体により規制を受ける場合があります。それぞれの自治体規制に従って廃棄してください。
- lithium 一次電池(過塩素酸塩含有量が6ppb以上)を組み込んだ製品が米国-California 州へ輸出・経由される場合、次の表示が義務化されています。  
Perchlorate Material – special handling may apply. See <http://www.dtsc.ca.gov/hazardouswaste/perchlorate>
- 形 CP1L-□□□□-□は lithium 一次電池(過塩素酸塩含有量が6ppb以上)を搭載しています。形 CP1L-□□□□-□が組み込まれた貴社製品を米国-California 州へ輸出される場合は、貴社製品の梱装箱、輸送箱などに上記表示を行っていただくようお願いします。
- この商品は PLC システムに組み込まれた状態で、EMC 指令に適合しています。EMC 指令に適合するための、接地-ケーブル選定-その他の条件については、該当するマニュアルを参照ください。
- この商品は「class A」(工業環境商品)です。住宅環境でご利用されると、電波妨害の原因となる可能性があります。その場合には電波妨害に対する適切な対策が必要となります。
- 形 CP1W-DAM01 の表示画面やボタンを、ドライバなど鋭利なもので押さないでください。



「廢電池請回收」

## オプション製品の取扱い

- 以下の各種オプション製品は、必ず PLC に装着して使用します。

オプション製品	適用 PLC	
RS-232C オプションボード 形 CP1W-CIF01	CP1L CPU ユニット 形 CP1L-□□□□-□	CP1H CPU ユニット 形 CP1H-□□□□-□
RS-422A/485 オプションボード 形 CP1W-CIF11/CIF12		
データアクセスモジュール 形 CP1W-DAM01		
メモリカセット 形 CP1W-ME05M		
I/O 接続ケーブル 形 CP1W-CN811		
CJ ユニットアダプタ 形 CP1W-EXT01		

## CJ ユニット接続時のお願い

- CJ ユニットアダプタを用いて、CJ シリーズの高機能 I/O ユニット、CPU 高機能ユニットを接続するときは、ユニット同士を接続後、上下のスライダーをカチッと音がするまでスライドさせて、確実にロックしてください。ロックしないと機能が満足できないことがありますので注意してください。
- CJ ユニットアダプタに付属されているエンドカバーは、必ず最右端の CJ シリーズのユニットに取り付けてください。エンドカバーを取り付けないと正常に動作しません。

## 使用上の注意

- 参照マニュアルに示すとおり、正しく設置してください。
- 次のような環境には設置しないでください。
  - ・日光が直接当たる場所
  - ・周囲温度や相対湿度が仕様値の範囲を超える場所
  - ・温度の変化が急激で結露するような場所
  - ・腐食性ガス、可燃性ガスのある場所
  - ・ちり、ほこり、塩分、鉄粉が多い場所
  - ・水、油、薬品などの飛沫がかかる場所
  - ・本体に直接振動や衝撃が伝わる場所
- 次のような場所で使用する際は、遮蔽対策を十分に行ってください。
  - ・静電気などによるノイズが発生する場所
  - ・強い電界や磁界が生じる場所
  - ・放射能を被曝する恐れのある場所
  - ・電源線や動力線が近くを通る場所

## 参照マニュアル

形式/マニュアル名称		Man. No.
SYSMAC CP シリーズ CP1H	ユーザーズマニュアル	SBCA-340
SYSMAC CP シリーズ CP1L	ユーザーズマニュアル 導入編	SBCA-344
SYSMAC CP シリーズ CP1L	ユーザーズマニュアル	SBCA-345
SYSMAC CP シリーズ CP1H/CP1L	プログラミングマニュアル	SBCA-341
SYSMAC CS/CJ/CP シリーズ	通信コマンドリファレンス	SBCA-304
SYSMAC CS/CJ シリーズ シリアルコミュニケーションボード/ユニット 形 CJ1W-SCU21-V1/41-V1	ユーザーズマニュアル	SBCD-300
SYSMAC CS/CJ シリーズ Ethernet ユニット 形 CJ1W-ETN11	ユーザーズマニュアル	SBCD-307
SYSMAC CS/CJ シリーズ Ethernet ユニット (100BASE-TX タイプ) 形 CS1W-ETN21、形 CJ1W-ETN21	ユーザーズマニュアル 基本ネットワーク構築編 アプリケーション構築編	SBCD-329 SBCD-330
DeviceNet	ユーザーズマニュアル	SCCC-308
SYSMAC CS/CJ シリーズ DeviceNet ユニット	ユーザーズマニュアル	SBCD-314
CompoBus/S マスタユニット 形 CJ1W-SRM21	ユーザーズマニュアル	SCCC-307
スレーブ 形 SRT1/SRT2 シリーズ		
SYSMAC CS/CJ シリーズ Controller Link ユニット (ワイヤタイプ) 形 CJ1W-CLK21-V1、 リピータユニット 形 CS1W-RPT01/02/03	ユーザーズマニュアル	SCCC-326
SYSMAC CS/CJ シリーズ プロセス入出力ユニット 形 CJ1W-PTS□□/PDC□□	ユーザーズマニュアル	SBCC-826
SYSMAC CS/CJ シリーズ アナログ入・出力ユニット 形 CJ1W-AD□□/DA□□/MA□□	ユーザーズマニュアル	SBCC-820
SYSMAC CJ シリーズ 温度調節ユニット 形 CJ1W-TC□□□	ユーザーズマニュアル	SBCC-830
SYSMAC CJ シリーズ 高速カウンタユニット 形 CJ1W-CT021	ユーザーズマニュアル	SBCC-831
SYSMAC CJ シリーズ 位置制御ユニット 形 CJ1W-NC□□□	ユーザーズマニュアル	SBCE-315
SYSMAC CJ シリーズ 位置制御ユニット 形 CJ1W-NCF71	ユーザーズマニュアル	SBCE-323
SYSMAC CJ シリーズ モーションコントローラユニット 形 CJ1W-MCH71	ユーザーズマニュアル	SBCE-327
CX-Programmer (Ver.7.1) 形 WS02-CXPC1-JV7	オペレーションマニュアル オペレーションマニュアル ファンクションブロック編	SBCA-337 SBCA-338
CX-Net 形 WS02-CXPC1-JV7	オペレーションマニュアル	SBCA-331
CX-Protocol Ver. 1.7 形 WS02-PSTC1-J□	オペレーションマニュアル	SBCA-307
CX-Simulator Ver. 1.7 形 WS02-CIMC1-J□	オペレーションマニュアル	SBCA-310

## ご使用に際してのご承諾事項

下記用途に使用される場合、当社営業担当者までご相談のうえ仕様書などによりご確認いただくとともに、定格・性能に対し余裕を持った使い方や、万一故障があっても危険を最小にする安全回路などの安全対策を講じてください。

- 屋外の用途、潜在的な化学的汚染あるいは電氣的妨害を被る用途またはカタログ・取扱説明書などに記載のない条件や環境での使用
  - 原子力制御設備、焼却設備、鉄道・航空・車両設備、医用機械、娯楽機械、安全装置、および行政機関や個別業界の規制に従う設備
  - 人命や財産に危険が及ぶシステム・機械・装置
  - ガス、水道、電気、電気の供給システムや 24 時間連続運転システムなど高い信頼性が必要な設備
  - その他、上記 a) ~d) に準ずる、高度な安全性が必要とされる用途
- \* 上記は適用用途の条件の一部です。当社のベスト、総合カタログ、データシート等最新版のカタログをよく読んでご使用ください。

## オムロン株式会社 営業統轄事業部

東京都品川区大崎1-11-1 ゲートシティ大崎ウエストタワー14F (〒141-0032)

●営業にご用の方も、技術お問い合わせの方も、フリーコールにお電話ください。  
音声ガイダンスが流れますので、案内に従って操作ください。

フリーコール **0120-919-066** オムロン

携帯電話・PHS等移動通信からのお電話は、お手数ですが、  
TEL 055-982-5015 (通話料がかかります)へおかけください。

【技術のお問い合わせ時間】  
■営業時間:9:00~12:00/13:00~19:00  
(土・日・祝祭日は9:00~12:00/13:00~17:00)  
■営業日:年末年始を除く  
上記フリーコール以外に、055-977-6389 (通話料がかかります)  
におかけいただくことにより、直接FAシステム機器の技術窓口につながります。

【営業のお問い合わせ時間】  
■営業時間:9:00~12:00/13:00~17:30 (土・日・祝祭日は休業)  
■営業日:土・日・祝祭日/春期・夏期・年末年始休暇を除く

お断りなく仕様などを変更することがありますのでご了承ください。